ProGrip8 Radio Remote Control

	System Part Number: **UBRF-PG8-10**
	Radio Remote Control System consisting of ProGrip8 Radio Transmitter & DC10 Radio Receiver Unit with N/O Momentary Relay Outputs. AC Transmitter Charger included.

Standard System Package: (Customised label options available for ProGrip Transmitter to include button functions and company logo. Protective Bumper can also be supplied in Yellow, Green or Grey)

1 x UBRF-PG8-10 includes:

UB/PRO8/433/TX01	**UB/RX/DC10/401**	**PA31/CHARGER/01**
		

Part Numbers:

UBRF-PG8-10	**ProGrip8 Radio Remote Control System**	
UB/PRO8/433/TX01	**ProGrip8 Radio Transmitter**	
PA31/CHARGER/01	**AC Transmitter Charger (DC optional)**	
UB/RX/DC10/401	**DC10 Radio Receiver Unit**	

Optional Accessories:

PA31/CHARGER/02	**DC Transmitter Charger**	
PA08/BOP/005	**Lanyard Loop & Lanyard for ProGrip**	
PA08/BOP/006	**Universal Belt-Clip for ProGrip**	
PA08/BOP/013	**Wall Holder for ProGrip**	

Technical Specifications

ProGrip8 Radio Transmitter

Number of buttons:	8
Battery type:	3 x AA (Rechargeable LiPo)
Dimensions:	159.4 x 77.9 x 35.5mm
Weight:	240g
IP Protection rating:	IP65
Operating temperature:	-20 °C to +55 °C
Transport/storage temperature:	-40 °C to +70 °C
Antenna:	Internal
Operating distance range:	Up to 150 metres
Operating radio frequency band:	433.075-434.775MHz

DC10 Receiver Unit

Power supply:	12-24 VDC
Outputs:	10
Max voltage to contacts:	12A @ 250VAC & 24VDC
Dimensions:	201.0 x 122.4 x 55.0mm
IP protection rating:	IP65
Operating temperature:	-20 °C to +55 °C
Transport/storage temperature:	-40 °C to +70 °C
Antenna:	External Antenna on 3 metre cable (pre-fitted)
Operating radio frequency band:	433.075-434.775MHz



FSL Electronics Ltd
Unit 9 Kilcronagh Business Park, Cookstown BT80 9HJ
+44 (0)28 867 66131 | info@fslelectronics.com
FSLELECTRONICS.COM